

Ice Cold Beer/Zeke's Peak Power Supply Conversion Kit

Copyright 2003-2019 Arcadeshop, LLC - all rights reserved.

Although this upgrade has been tested and the techniques used will not directly cause harm to your game. If you do something wrong, you can very seriously damage the electronics! So...



WARNING



...Please read the instructions.

To perform this upgrade, you should:

- Have a working understanding of electronics.
- Be familiar with safe handling procedures for electronic components.
- Be able to follow directions.

Anytime you start messing around with something (particularly something electronic) you accept a certain amount of risk that you may break something. This kit carries with it no guaranty of compatibility to your particular game. If you carefully follow these instructions, you'll do fine and everything will work. If this looks like it's above your confidence level please recruit someone to install the kit for you!

Introduction

Congratulations! You now have the power supply conversion kit which should bullet proof your game. The original power supply could be rebuilt, but a new switching power supply is power efficient, has built in shut down protection and runs cooler.

Before we get started, grab your favorite beverage, maybe something to snack on, and find a quiet place to read this manual so you fully understand what to do before you start tinkering around with your precious labor of love!

Necessary Parts and Tools:

You will need the following parts/tools for this upgrade...

- Phillips Screwdriver
- Pliers
- Soldering Iron

Step One: Unplug the game from its power source!



While installing this kit, electric shock is possible if power is present!

Step Two: Disconnect old power supply

The original power supply board is mounted at the bottom of the cabinet on the transformer assembly, unplug the connector at location J3 from the old power supply board.

Step Three: Assemble and mount new power supply

In this step, you will need to attach the adapter and A.C. Power wires to the new switching power supply. (See page 1) Next, simply mount the new power supply in a convenient location and connect the connector J3 to the new adapter. Be sure the connector is plugged in the correct way by matching the keyed pin on the new power adapter.

Locate the two A.C. power wires leading to the fluorescent light fixture. Find a convenient location and tap the two wires from the new power supply to each of the light fixture power wires.

Next, solder the Red wire to TP8 (Test Point 8) on the game pcb. The two jumpers on the adapter are for disabling the +5 voltage (the Red wire).



Step Four: Check your work

Verify all connectors and be sure everything is secure. You may need to adjust the +5 volts to +5.05 volts.

You have installed the kit – congratulations!

Final Notes:

This kit carries with it no guaranty of compatibility to your particular game. Although this kit has been tested with numerous games, there is a possibility that some of them are different. This kit carries no liability protection for you game, while there is no reason this kit should cause damage to your game, it is possible that incorrect or poor wiring can damage your game board(s). Liability is limited to repair/replacement of the Kit only.